
ADJUSTMENTS OF PC BDARD (METAL BLACK 625 0D673A)

6-CONNECTOR



☆ CONTROL DE THIS GAME USES DNE 8-WAY JOYSTICK AND TWO BUTTONS.

NDTF) BFFDRE CHANGING THE SETTING OF DIP SWITCH, TURN THE POWER DEF.

SDLOFR SIDE			CDMPDNENTS SIDE
GND	Α	1	GND
GND	B	2	GND
+5V	С	3 4	+5V
+5V	D	4	+5V
-5 V	F	5	- 5 V
+12V	F	.6_ 7	+12V
POST	Н		POST
COIN METER 2	j	8	COIN METER 1
CDIN LDCKOUT 2	K	9	COIN LOCKDUT T
SPEAKER (-)	L	10	SPEAKER (+)
SOUND GND	М	11	SOUND
VIDEO G	N	12	VIDEO R
VIDED SYNC	Р	1.13	VIDED B
SERVICE SW	R	214	VIDED GND
TILT SW	S T -	15	
COIN 2	Τ -	1.6	. COTN 1
2P SELECT	U,	7	1P SELECT
2P ÜP	٧.	18	. 1P UP
2P DDWN	Wit		*1P ODWN
2P LEFT			表/1P LEFT
2P RIGHT	À.	215	TAE 1P RIGHT
2P A-BUTTON	Z	22	IP A-BUTTON
2P_B-BUTTON	а	23	TP B-BUTTON
	b	2-4	•
	c	25	
	d	26	
GNO	ě.	27	- GNO
GNO	~f	28	# GND

\Diamond	SETTING DF	OIP S	WITCH A				٠,	. "" -	***	*):FA(CTDRY S	ETTING
Г	SETTINGS		Ρ	OSITIONS :	1	2	3	4	5	6	7	8
	CORETA DAT	4.7.TO.41	* NDRMAL			DFF						
	SCREEN MATATION		REVERSE	REVERSE		DN						
			* NORMAL GA	MF	0FF	AFE	OFF					
			TEST MODE				DN					
	ATTRACT SDI	NAI O	* WITH					OFF				
1		טאט	WITHOUT				_	DN				
	FOR NORTH AMERICA EXC				EPT ND	RTH AM	ERICA					ĺ
		* 1 0	DIN 1 PLAY	PLAY	*	* 1 CDTN 1 PLAY 2 COINS 1 PLAY				DFF		
	PLAY	2 0	OINS PLAY	PRICING								
	PRICING	3 0	DINS 1 PLAY	CDIN A		3 CDTNS 1 PLAY			DFF	DN		- 1
		4 C	OINS 1 PLAY	ODIN A		4 CDTN	IS 1 PL	AY.	DN	Би		
Γ	BUY-IN	*	P	PLAY PRICING CDIN B	*	1 CDIN	2 PL	.AYS			OFF	OFF
	PLAY	1 0	OIN CONTINUE			1 COIN	: 3 PL	AY\$			ON	011
	PRICING	1 2 CD1	DTNS CONTINUE			1 CDTN 4 PLAYS		AYS			DFF	DN
	LUTOTHO	3 0	DINS CONTINUE	PDIN D		1 COIN	6 PL	AYS.			DN	D.11

1. . THIS SETTING SHOULD BE THE SAME SETTING AS THAT DF "PLAY PRICING".

SETTING DE DIP SWITCH B

SETTINGS	POSITIONS	1	2	3	4	5	6	7	8
GAME OIFFICULTY EASY(A) → DIFFTCULT(O)	* RANK B	OFF	DFF						
	RANK A	ON							
	RANK C	DFF	- ON						
	RANK D	DN							
BDNUS EXTEND (1 UP) K=1.000PTS.	* 70K/22DK/370K/520K/670K/820K····			DFF	OFF	1			
	50K/170K/290K/410K/530K/650K····			ON					
	80K/240K/400K/56DK/720K/880K····			DFF	0.11	1 .			
	1DDK/30DK/50DK/700K/900K/1100K···				ON				1
	* 3					OFF	OFF		
NUMBER OF	4					ON	UFF.	J	
PLAYER(S)	2_					0FF	- DN	}	
	1					DN	וייי		1
CONTINUE MDDE	* WTTH							DFF	1
	WITHOUT							DN	
GAME TYPE	* DOUBLE CONTROL PANEL								DFF
	STNGLE CONTROL PANEL	. (DNLY 1P)						DN	